

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
22 January 2004 (22.01.2004)

PCT

(10) International Publication Number
WO 2004/008207 A1

(51) International Patent Classification⁷: G02B 6/28, 6/125

Frederick, Marcel [NL/GB]; Alcatel Optronics UK Limited, Starlaw Park, Starlaw Road, Livingston, West Lothian EH54 8SF (GB).

(21) International Application Number:
PCT/GB2003/003028

(22) International Filing Date: 11 July 2003 (11.07.2003)

(74) Agent: McDONOUGH, Johnathan; Urquhart-Dykes & Lord, Tower House, Merrion Way, Leeds LS2 8PA (GB).

(25) Filing Language: English

(81) Designated States (*national*): CN, JP, US.

(26) Publication Language: English

(30) Priority Data:
0216319.4 13 July 2002 (13.07.2002) GB

(84) Designated States (*regional*): European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR).

(71) Applicant (*for all designated States except US*): ALCA-
TEL OPTRONICS UK LIMITED [GB/GB]; Starlaw
Park, Starlaw Road, Livingston, West Lothian EH54 8SF
(GB).


Published:
— with international search report

(72) Inventor; and

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(75) Inventor/Applicant (*for US only*): VAN DER VLIET,

(54) Title: IMPROVED OPTICAL SPLITTER WITH TAPERD MULTIMODE INTERFERENCE WAVEGUIDE



(57) Abstract: A 1 x 2 splitter design having low loss is described. The splitter has a non-adiabatic tapered waveguide (22) connected between a substantially single-mode input waveguide (20) and two output waveguides (24, 26). The non-adiabatic tapered waveguide widens in width towards the output waveguides, and merges substantially continuously with the input waveguide in a direction parallel to the optical axis of the input waveguide. This keeps radiation mode generation to a minimum which, in turn, keeps insertion loss low. In the described embodiment, the non-adiabatic taper shape is based on a perturbed cosine function. The 1 x 2 splitter can be cascaded with other such splitters in order to build a 1 x 2N splitter design.

INTEGRATED OPTICAL SPLITTER WITH TAPERED MULTIMODE INTERFERENCE WAVEGUIDE

The present invention relates to a branching or "splitter" waveguide structure. In particular, the invention relates to a 1x2 splitter having low
5 loss.

1 x 2 splitters in the form of adiabatic Y-junction or Y-branch waveguide structures are well known and used in planar lightguide circuits (PLCs). Fig.1 shows a conventional y-branch splitter in which a single-mode input waveguide 1 branches into two single mode output waveguide
10 2,3 at a Y-junction 4. Where the branching ratio is 1:1 we call this a symmetric Y-branch. Such Y-branch structures can be arranged in a cascaded arrangement to form a 1×2^N splitter, as illustrated in Fig.3 (which shows a 1 x 16 splitter). A problem with the Y-branches is that it is very difficult in practice to fabricate a perfect point 5 in the Y-junction, where
15 the two output waveguides 2,3 meet. In practice, instead of a perfect point, a flat edge or "blunt" 6 is formed, as shown in Fig 2. In fact, in order to meet required manufacturing tolerances in order to make a reproducible device, the splitter will commonly be purposely designed to have the blunt taper shape 4 shown in Fig.2. A disadvantage of this blunt is that radiation
20 modes are excited at the blunt, leading to insertion loss. In a 1×2^N splitter such as shown in Fig. 2 the insertion loss at each Y-branch may add up to an unacceptably high total insertion loss (IL) in the splitter device. Moreover, the generation of radiation modes results in reduced Insertion Loss uniformity (ILU) i.e. the variation of the IL as a function of
25 wavelength, across the operational wavelength range of the device.

Another type of splitter is based on a multi-mode interferometer (MMI) waveguide. Fig.4 shows a 1 x 2 splitter formed by coupling an MMI
10 between a single mode input waveguide 1 and two single-mode output waveguides 2,3. This non-adiabatic device works on the principle that the

MMI converts the single-mode input signal into a double-peaked signal before the branches of the splitter start, so that the two peaks enter the two output waveguides respectively. Such MMI-based splitters have higher fabrication tolerances than the Y-branch splitters of Fig.1. However, they have the disadvantage that the abrupt junction between the input waveguide and the input edge 12 of the MMI 10 gives rise to radiation modes, and thus insertion loss.

A low radiation loss asymmetric splitter is proposed in US 6,236,784. This shows an MMI-based splitter design in which one or both sides of the MMI have a curved shape along the signal propagation direction. However, this structure still used an abrupt transition between the input waveguide and the MMI in order to generate the higher order modes which create the desired double-peaked field at the output edge of the MMI, and so the problem of radiation loss at this abrupt transition is still present.

It is an aim of the present invention to avoid or minimise one or more of the foregoing disadvantages.

According to the present invention there is provided a splitter comprising: a substantially single-mode input waveguide; at least two output waveguides; and a non-adiabatic tapered waveguide optically coupled between the input waveguide and the output waveguides, said waveguides being formed on a substrate; wherein the non-adiabatic tapered waveguide, along at least a portion of its length, widens in width towards the output waveguides, in a plane parallel to the substrate, and the non-adiabatic tapered waveguide merges substantially continuously with the input waveguide in a direction parallel to the optical axis of the input waveguide.

The splitter of the invention has the advantage that there is no abrupt transition between the input waveguide and the multi-mode region, and so

generation of radiation modes is minimized, thereby reducing insertion loss and improving the insertion loss uniformity. Moreover, the splitter can in general be designed to be shorter in length (along the propagation direction) than an adiabatic Y-branch splitter, as the non-adiabatic tapered waveguide is itself shorter than an adiabatic tapered waveguide would be. This has obvious cost advantages in terms of PLC chip real estate.

Preferably, the non-adiabatic waveguide tapers gradually so as to excite a second order mode therein.

The non-adiabatic tapered waveguide preferably tapers substantially symmetrically with respect to an extension of the optical axis of the input waveguide. The non-adiabatic tapered waveguide may have opposing tapered sides each having a taper shape based on a perturbed cosine curve.

Optionally, at least one of the output waveguides may have an adiabatically tapered end which is connected to the non-adiabatic tapered waveguide and which widens in width, or which narrows in width, towards the non-adiabatic tapered waveguide.

Preferred embodiments of the invention will now be described by way of example only and with reference to the accompanying drawings in which:

Fig.1 is a plan view of a prior art Y-branch 1 x 2 splitter;

Fig.2 is a detailed view of the ringed portion A of the Y-branch splitter of Fig.1, showing a blunt formed in the fabrication process;

Fig.3 is a plan schematic view of a 1×2^N splitter, where $N=4$;

Fig.4 is a plan view of a prior art 1 x 2 MMI-based splitter;

Fig.5 is a plan view of a 1 x 2 splitter according to an embodiment of the present invention;

Fig.6 is a plan schematic view of a non-adiabatic tapered waveguide having its shape defined by a perturbed cosine function;

Fig.7(a) to (c) illustrate the modified shape of the taper of Fig.6, obtained when three different shape factors, p , are used to perturb the cosine shape;

Fig.8 is a schematic plan view of a modified version of the splitter of Fig.5; and

Fig.9 is a perspective schematic view of a waveguide formed in a PLC chip.

Fig.5 illustrates a 1 x 2 splitter formed in a Planar Lightguide Circuit (PLC) chip 18. The splitter comprises a single-mode input waveguide 20 coupled to two output waveguides 24,26 by a non-adiabatic tapered waveguide 22. The output waveguides each consist of a single mode waveguide having an adiabatically tapered end portion 25,27 coupled to the wide (output) end 23 of the non-adiabatic tapered waveguide 22, such that the output waveguides widen towards the non-adiabatic tapered waveguide, in plan view of the splitter as shown in Fig. 5. As can be seen in Fig.5, the taper shape is such that the width of the waveguide 22 gradually increases, in a generally non-linear manner, from the input end 21 coupled to the input waveguide 20, to the output end 23 coupled to the two output waveguides. Where this splitter is the first optical circuit feature on the PLC chip 18, as shown in Fig.5, an input end 19 of the input waveguide 20 will abut the input face 17 of the PLC chip. The taper shape of the non-adiabatic tapered waveguide 22 is generally designed to cause continuous mode conversion, of the fundamental mode to the second order mode, of an input signal entering the input end 21 of the tapered waveguide from the input waveguide 20, along the length L of the taper 22, to form a double-peaked mode field at the output end 23 of the taper 22. In the embodiment of Fig.5, the shape of the non-adiabatic tapered waveguide is based on a perturbed cosine function, and is defined by the following equations (with reference to Fig.6):

$$w(t) = w_{in} + \frac{w_{out} - w_{in}}{2} [1 - \cos(2\pi t)]$$

$$z(t) = L \left[t + \frac{p}{2\pi} \sin(2\pi t) \right]$$

$$t = [0..1]$$

where L is the length of the non-adiabatic tapered waveguide 22;

w(t) is the width along the propagation direction;

z(t) is the length along the propagation direction;

5 w_{in} and w_{out} are the widths of the input and output ends 21,23 respectively of the tapered waveguide 22; and p is a shape factor, which preferably has a value between 0 and 1, most preferably between 0.6 and 0.9, and which basically controls the slope in the middle ($z=0.5L$) of the taper (values of p greater than 1 are also possible, though less
10 preferred).

In the splitter of Fig.5, the width w_{in} of the input waveguide (and hence also of the input end 21 of the non-adiabatic taper 22) is G_W, which in this embodiment is equal to the width of the single mode portion of each of the two output waveguides 24,26 (in other possible
15 embodiments the width of the input and output waveguides can be different, if desired for any reason). Other variables in the splitter design of Fig.5 include:

G, the width of the gap or "blunt" formed between the adjacent edges of the two output waveguides 24,26 at the output end 23 of the non-
20 adiabatic tapered waveguide 22;

R, the radius of curvature of each output waveguide;

dWBranch, the additional width of the tapered end 25,27 of each output waveguide, as compared with the width G-W of the single mode portions of these output waveguides;

dWTap, the additional width of the output end 23 of the non-adiabatic taper, as compared with the total width of the two adiabatically tapered output waveguide ends and the gap width G;

Lin, the length of the input waveguide.

- 5 For a given w_{in} and w_{out} , the free parameters in the taper shape are L and p. For different p values, the taper shape changes. This is illustrated in Figs.6(a) to (c) which show the taper shape for $p=0$, $p=0.5$ and $p=1$ respectively. L and p are chosen so that the phase difference between the zero and second order modes, at the output end 23 of the non-adiabatic
- 10 taper, is equal to an odd multiple of π (i.e. π , 3π , 5π ..etc). This gives a straight phase front which will reduce coupling losses to the output waveguides 24,26. π is the preferred value as this will give the shortest taper length. Beam Propagation Mode (BPM) simulations are used to choose the optimum values for the variables in the splitter design
- 15 (including to calculate the required value of p and L in order that the aforementioned phase condition is met by the non-adiabatic taper 22), so as to obtain a splitter design giving optimum performance in terms of the required specifications of the end device, in particular the insertion loss of the splitter.
- 20 A significant feature of the perturbed cosine tapered waveguide shape is that at the beginning 21 of the taper, where the taper 22 merges into the output end of the single mode input waveguide 20, the taper angle is kept low by virtue of the generally cosine curve shape of the taper at the beginning. This keeps radiation losses to a minimum. (For the avoidance of
- 25 doubt, the taper angle is defined as the angle of the tapered sides of the waveguide relative to the propagation direction in the waveguide. In the illustrated embodiments, where the waveguides have a generally symmetrical structure, the propagation direction is along the axis of the

waveguides.) The taper angle gradually increases towards the output waveguides until after the perturbation introduced by the factor p .

Another advantage of the invention, compared with conventional splitter designs like that of Fig.2, is that the width of the gap or blunt, G , between the output waveguides where they join to the cosine taper, can be made larger than the width of the blunt 6 in the conventional splitter design of Fig.2. In such conventional splitter designs the highest intensity is at the middle of the taper 4. (This is not the case in the present invention in which the output from the non-adiabatic taper is double-peaked.)

Therefore, in the conventional design of Fig.2 one would like to have the gap (blunt) between the output waveguides, at the output of the taper 4, as small as possible to reduce the losses. The desired smallness of this gap can lead to designs that are less tolerant to production tolerances e.g it is easier to make and to reproduce a gap of 2 micron compared to a gap of 1 micron.

For a conventional splitter design like that of Fig. 2 the optimum gap is 0, giving the splitter design of Fig.1. For the non-adiabatic cosine taper splitter of the present invention the optimum gap G is not equal to 0 and can be designed to be a number which can easily be manufactured and reproduced. A follow-on advantage of this is that the inventive splitter will be more tolerant, in terms of wavelength dependent loss (WDL), to process variations.

In known manner the waveguides in the PLC chip 18 are all typically formed as silica "cores" 32 on a silicon substrate 30 (an oxide layer 31 is commonly provided on the substrate prior to depositing the waveguide materials and/or a lower silica cladding layer 31 may be deposited) and are covered in a cladding material 34, using Flame Hydrolysis Deposition (FHD) or Chemical Vapour Deposition (CVD) fabrication processes (together with photolithography and etching steps). Fig.9 shows one such waveguide formed in a PLC chip 40. However the present invention is

equally applicable to waveguide devices formed in other material systems, or having a different waveguide structure e.g. rib waveguides.

It will be appreciated that the splitter design of Fig.5 can be cascaded with several identical such 1 x 2 splitters in a similar manner as shown in Fig.3, in order to obtain a 1 x 2^N splitter, where $N=2,3,4,\dots$. The use of the perturbed cosine taper shape in each 1 x 2 splitter keeps the total insertion loss for the resulting 1 x 2^N splitter to a minimum.

Modifications to the above-described embodiment are of course possible within the scope of the invention. For example, the single-mode output waveguides may in some cases not be tapered 25,27 where they connect to the perturbed cosine taper 22. Nevertheless, the use of tapers at these ends of the output waveguides is generally preferred. This is because such tapers allow an increase in the overlap of the double-peaked field (combination of zero and second order modes) at the output (i.e. wide) end of the cosine taper 22 with the field of the two output waveguides at the transition point (where the output waveguides join to the cosine taper waveguide 22). The field will change shape with a change in the width of the output waveguides at the transition point. There will be an optimal width (and gap, G) to obtain a maximum overlap. Adiabatic tapers on the output waveguides are preferred as they minimise any further energy losses.

In another possibility there may be a small gap g (for example, about 1 μm) provided between each output waveguide 24,26 and the output end 23 of the non-adiabatic tapered waveguide 22, as shown in Fig.8. This is done for process reasons as it is believed to achieve a better definition of the gap G , between the output waveguides (at the wide end of the non-adiabatic tapered waveguide) and so improve the production tolerances.

In the embodiment of Fig.5 the input waveguide is a single-mode waveguide. In other embodiments the input waveguide may be allowed to be slightly double-moded (bi-modal) as long as no significant signal is effectively carried by the higher order modes (i.e. modes above the
5 fundamental mode). In both cases we consider such a waveguide as being a “substantially single mode” waveguide. The output waveguides are preferably always substantially single-mode, but could be multi-mode if desired for any reason. In another possibility, the input waveguide could be a bi-modal waveguide in which only a first order signal mode propagates,
10 but this is not preferred as it is likely to lead in practice to unpredictable performance of the device (due to any process-related imperfections in the waveguides which may result in undesirable mode conversion to higher order modes).

In another possible modified version of the device of Fig.5, the
15 tapered ends 25, 27 of the output waveguides 24,27 may narrow in width towards the non-adiabatic tapered waveguide 22 instead of widening as shown in Fig.5. A decreasing width will widen the modal field distribution in the waveguide, giving a similar effect (on the optical signal) as a widening width.

20 Furthermore, in other possible embodiments the non-adiabatic tapered waveguide 22 need not continue to widen in width along its entire length L until it joins with the output waveguides as in the Fig.5 embodiment. For example, the non-adiabatic waveguide may, if desired, widen towards the output waveguides along a majority of its length and
25 then may start narrowing in width before it joins the output waveguides. This will however result in the total length of the splitter being longer than in the Fig.5 embodiment.

Also, in the embodiment of Fig.5 the output waveguides 24,26 do not have to bend in an arc shape with radius R : other curves are possible.

CLAIMS

1. A splitter comprising:
 - a substantially single-mode input waveguide;
 - 5 at least two output waveguides; and
 - a non-adiabatic tapered waveguide optically coupled between the input waveguide and the output waveguides;
 - said waveguides being formed on a substrate; wherein
 - the non-adiabatic tapered waveguide, along at least a portion of its
 - 10 length, widens in width towards the output waveguides, in a plane parallel to the substrate, and
 - the non-adiabatic tapered waveguide merges substantially continuously with the input waveguide in a direction parallel to the optical axis of the input waveguide.
 - 15
2. A splitter according to claim 1, wherein at least an initial portion of the non-adiabatic tapered waveguide proximal to the input waveguide has a taper angle which increases towards the output waveguides.
- 20 3. A splitter according to claim 1 or claim 2, wherein the non-adiabatic waveguide tapers gradually so as to excite a second order mode therein.
4. A splitter according to claim 3, wherein the length of the non-adiabatic tapered waveguide, in a direction parallel to the direction of propagation
- 25 of an optical signal therein, is such that the phase difference between the fundamental and second order modes, at an output end of the non-adiabatic tapered waveguide is equal to $M\pi$ where $M=1,3,5,\dots$.

5. A splitter according to any preceding claim, wherein the non-adiabatic tapered waveguide tapers substantially symmetrically with respect to the direction of propagation of an optical signal therein.
- 5 6. A splitter according to claim 5, wherein the non-adiabatic tapered waveguide has opposing tapered sides each having a taper shape based on a perturbed cosine curve.
7. A splitter according to any preceding claim, wherein said output
10 waveguides are substantially single mode waveguides.
8. A splitter according to claim 7, wherein at least one of the output waveguides has an adiabatically tapered end which is connected to an output end of the non-adiabatic tapered waveguide and which widens in
15 width towards the non-adiabatic tapered waveguide.
9. A splitter according to any of claims 1 to 7, wherein there is a gap between an output end of the non-adiabatic tapered waveguide and respective ends of the output waveguides optically coupled thereto.
20
10. A 1×2^N splitter, where $N=2,3,4,\dots$, comprising a plurality of splitters according to any preceding claim.
11. A 1×2 splitter substantially as described herein with reference to Fig.5.
25
12. A 1×2 splitter substantially as described herein with reference to Fig.8.

-1/4-




FIG. 1
PRIOR ART




FIG. 2
PRIOR ART




FIG. 3
PRIOR ART

-2/4-




FIG. 4
PRIOR ART




FIG. 5

-3/4-




FIG. 6




FIG. 7(a)




FIG. 7(b)




FIG. 7(c)

-4/4-




FIG. 8




FIG. 9

INTERNATIONAL SEARCH REPORT

International Application No

PCT/GB 03/03028

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 G02B6/28 G02B6/125

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 G02B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the International search (name of data base and, where practical, search terms used)

EPO-Internal, INSPEC

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 6 236 784 B1 (IDO TATEMI) 22 May 2001 (2001-05-22) cited in the application figure 15	1-8
Y	column 14, line 45 - line 48 column 17, line 30 - line 34 column 12, line 13 column 8, line 4 - line 6 column 14, line 63 - line 66 ---	9,10
Y	EP 0 811 860 A (LUCENT TECHNOLOGIES INC) 10 December 1997 (1997-12-10) page 6, line 3 - line 9 figure 7 --- -/--	9,10

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the International filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the International filing date but later than the priority date claimed

- *T* later document published after the International filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *G* document member of the same patent family

Date of the actual completion of the International search

20 October 2003

Date of mailing of the International search report

05/11/2003

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Orignac, X .

INTERNATIONAL SEARCH REPORT

Internat. Application No
PCT/GB 03/03028

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT		
Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	GB 2 368 131 A (MARCONI CASWELL LTD) 24 April 2002 (2002-04-24) figure 3 page 7, line 24 - line 26 page 7, line 18 - line 20 page 7, line 1 - line 2 page 7, line 28 - line 33 ---	1-10
X,P	KEH-YI LEE, JAU-ANN SHEN, WEI-CHIH TSAI, FU-CHIANG CHANG, KUO-CHANG LO: "New type of 1x3 MMI optical power dividers with reverse taper section" JOURNAL OF OPTICAL COMMUNICATIONS, XP009019114 figure 1 ---	1-7
A	ZIRNGIBL M ET AL: "EFFICIENT 1 X 16 OPTICAL POWER SPLITTER BASED ON INP" ELECTRONICS LETTERS, IEE STEVENAGE, GB, vol. 28, no. 13, 18 June 1992 (1992-06-18), pages 1212-1213, XP000301390 ISSN: 0013-5194 figure 1 ---	8
A	KRUEGER S ET AL: "Design and realization of a novel polymer-based single-mode integrated optical beam splitter" MOEMS AND MINIATURIZED SYSTEMS, SANTA CLARA, CA, USA, 18-20 SEPT. 2000, vol. 4178, pages 77-87, XP002257830 Proceedings of the SPIE - The International Society for Optical Engineering, 2000, SPIE-Int. Soc. Opt. Eng, USA ISSN: 0277-786X figure 8 ---	6
A	LORENZO R M ET AL: "Improved self-imaging characteristics in 1 Nmultimode couplers" IEE PROCEEDINGS: OPTOELECTRONICS, INSTITUTION OF ELECTRICAL ENGINEERS, STEVENAGE, GB, vol. 145, no. 1, 20 February 1998 (1998-02-20), pages 65-69, XP006011325 ISSN: 1350-2433 figure 1 ---	1-5
P,A	US 2002/114572 A1 (BOUDA MARTIN) 22 August 2002 (2002-08-22) abstract --- -/--	

INTERNATIONAL SEARCH REPORT

Internatⁿ Application No
PCT/GB 03/03028

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
P,X	DE 101 21 007 A (PHOTEON TECHNOLOGIES GMBH BREG) 14 November 2002 (2002-11-14) figure 1 -----	1-8

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No
PCT/GB 03/03028

Patent document cited in search report		Publication date		Patent family member(s)	Publication date
US 6236784	B1	22-05-2001	JP	2000121857 A	28-04-2000
EP 0811860	A	10-12-1997	US	5745619 A	28-04-1998
			EP	0811860 A2	10-12-1997
			JP	10073735 A	17-03-1998
GB 2368131	A	24-04-2002	AU	9572001 A	22-04-2002
			WO	0231556 A1	18-04-2002
US 2002114572	A1	22-08-2002	JP	2002243961 A	28-08-2002
DE 10121007	A	14-11-2002	DE	10121007 A1	14-11-2002